


CODING THE METER

Code meter before using it for the first time and every time you change to another vial of OneTouch® Ultra™ Test Strips.



STEP 1

Enter code mode.

Start with meter turned off. Insert test strip to turn on meter. All display segments will appear, followed by code number.



STEP 2

Match code numbers.

Compare code number on meter display with code number on test strip vial. If matching, begin testing. If not matching, see Step 3.




STEP 3

Code meter.

Press C button until codes match. After Δ appears, meter is ready for testing.


USING THE METER MEMORY



STEP 1

Enter memory mode.


Start with meter turned off. Press M button. When you see 14-day average followed by 30-day average, you are in memory mode.



STEP 2

Recall test results.

After three seconds, most recent test result with date and time appears. Press C button once and next most recent test result will appear. Continue pressing C button to recall last 150 test results in order.



STEP 3

Exit memory mode.

Press M button to turn off meter.

TEST SUMMARY


Note: Before testing, wash hands with warm, soapy water. Rinse and dry thoroughly.



STEP 1

Insert test strip.



Push it in until it will go no further. Meter turns on automatically.



STEP 2

Apply sample.

Apply sample. When Δ symbol appears, touch and hold blood drop to narrow channel in top edge of test strip.



STEP 3

Fill confirmation window.

Be sure window is full before meter

counts down. If window is not full before meter begins countdown, repeat test with new test strip.




STEP 4

Accurate results in just 5 seconds.


DISPLAY SYMBOLS AND MESSAGES



The time flashing on the display indicated the meter lost power briefly and entered setting mode. Reset time, time format, and date as necessary. After setting meter, insert test strip. If --- appears on display, reset meter code. Test results stored in the meter memory may not be in the order in which they were performed. **Do not rely on 14- and 30-day averages.** Call OneTouch® Customer Careline for more information.



1) New meter not coded. Code meter; or 2) Meter lost power briefly and entered setting mode. Reset code number. Call LifeScan Customer Care for more information. **Possible meter memory problem; do not use 14- and 30-averages.**



Test result with suggestion to check ketone levels.




Blood glucose level higher than 33.3 mmol/L (600 mg/dL)




Blood glucose level lower than 1.1 mmol/L (20 mg/dL)




Temperature too low for testing. Repeat test when temperature/meter is above 6°C (43°F).




Temperature too high for testing. Repeat test when temperature/meter is below 44°C (111°F).




Battery power too low for testing. Replace battery immediately.





Problem with meter. Do not use the meter. Contact OneTouch® Customer Careline: UK (0800 121200), Ireland (1800 535676) for a replacement meter.




Used test strip inserted, or meter problem. Retest with a new test strip.



Blood or control solution applied before  appeared on display. Retest with a new test strip.



1) Possible high glucose in a test environment near low end of operating temperature range (6–44°C). Retest in a warmer environment.
Or, 2) Test strip damaged, moved during testing. Repeat test with new test strip.
Or, 3) Sample improperly applied. Review blood application and repeat test with new test strip.



Test strip damaged or confirmation window not full. Retest with a new test strip.
If problem persists, call OneTouch® Customer Careline: UK (0800 121200), Ireland (1800 535676).

LifeScan UK/Ireland,
A div. of Ortho-Clinical Diagnostics,
Johnson & Johnson,
50 - 100 Holmers Farm Way,
High Wycombe,
Bucks HP12 4DP
United Kingdom
www.LifeScan.co.uk

OneTouch® Customer
Careline:
UK (0800 121200)
Ireland (1800 535676)

ONETOUCH® Ultra™

BLOOD GLUCOSE MONITORING SYSTEM

QUICK REFERENCE GUIDE



IMPORTANT: Before testing, read detailed instructions in your OneTouch® Ultra™ Owner's Booklet. See inside for a quick review of instructions on coding the meter and the test procedure.



U.S. patents; other patents pending.
Rev: 2003/10
© LifeScan, Inc. 2002



AW 06038130A

Manufactured by

